

Linux

<https://wiki.debian.org/NetworkConfiguration>

<https://wiki.debian.org/InstallingDebianOn/Allwinner>

- [Kernel](#)
- [ubuntu18.4](#) [ubuntu20.4](#)
- [LXC](#)
- [Docker](#)
- [virtualbox](#)
- [GIMP](#)
- [multimedia](#)
- [wifi](#)

Preferences

Titlebar-Icons

```
gsettings set org.gnome.desktop.wm.preferences button-layout  
' :minimize,maximize,close'
```

Terminal-Width

```
stty rows 50 cols 150
```

if linebreak does not work this can help in ~/.bashrc:

```
shopt -s checkwinsize  
#if [ $(tty) == '/dev/ttyS0' ]; then  
#  trap resize DEBUG  
#fi  
#resize-befehl in xterm  
export PROMPT_COMMAND="resize &>/dev/null ; $PROMPT_COMMAND"
```

ppp ifup-script

Script in /etc/ppp/ip-up.d must not have extension [Quelle](#)

example: ppp-default-route in separate routing-Table:

```
PPP_LOCAL=$4  
PPP_REMOTE=$5  
PPP_IFACE=$1
```

```
ip route flush table telekom
ip route add $PPP_REMOTE/32 dev $PPP_IFACE src $PPP_LOCAL table telekom
ip route add default dev $PPP_IFACE table telekom
ip route show table telekom
exit 0
```

apt-get force ipv4

```
apt-get -o Acquire::ForceIPv4=true update
```

[Quelle](#)

permanent (as root):

```
echo 'Acquire::ForceIPv4 "true";' > /etc/apt/apt.conf.d/99force-ipv4
```

[Quelle](#)

basic x-server

```
apt-get install --no-install-recommends xserver-xorg xinit openbox
policykit-1 xterm xfonts-base
```

simple Mailserver

as Relay-Server (sending Mails over external Mailserver) for System-purposes (infos, backup,...)

<https://linuxundich.de/gnu-linux/system-mails-ohne-einen-mail-server-mit-ssmtp-verschicken/>

screen

<http://fractio.nl/2008/09/29/setting-session-name-in-screen/>

```
screen -S Sessionname command
```

wget

-P download in dir

```
wget <file.ext> -P /path/to/folder
```

-O download as file

```
wget <file.ext> -O /path/to/folder/file.ext
```

processinfo

```
ps -o pid,args -C tcpdump
```

nano

Jump to line: Ctrl+Shift+- (Ctrl+_)

Replace: Alt+R

settings

```
sudo nano /etc/nanorc
```

Cursorposition

```
## Constantly display the cursor position in the status bar. Note that  
## this overrides "quickblank".  
set constantshow #temporär strg+C,
```

linenumbers

```
## Display line numbers to the left of the text.  
set linenumbers # alt+# to disable temporarily
```

TAB-width

```
#/etc/nanorc  
set tabsize 4  
#temporary setting it (e.g. for Patches)  
nano -T 8 datei
```

storage check

```
#filesystem:
```

```
sudo fsck -f /dev/sdb1
#check for bad sectors
sudo badblocks -nsv /dev/sdb
```

NTP

```
apt-get install ntp
#nano /etc/ntp.conf # need restart after change
service ntp status
```

manual update:

```
service ntp stop
ntpdate ptbtime1.ptb.de
service ntp start
```

set time

```
#timedatectl --help
timedatectl set-timezone CET #timezone (CET/CEST)
date -s "2020-10-29 19:14" #time
hwclock -w #set RTC if there is any, else time will be wrong after next
reboot
```

update-alternatives

```
sudo apt-get install gcc-8-arm-linux-gnueabi
sudo update-alternatives --install /usr/bin/arm-linux-gnueabi-gcc arm-
linux-gnueabi-gcc /usr/bin/arm-linux-gnueabi-gcc-8 50
sudo update-alternatives --config arm-linux-gnueabi-gcc
arm-linux-gnueabi-gcc --version
```

other example

```
sudo update-alternatives --install /usr/bin/calc calc /usr/bin/gnome-
calculator 10
```

renaming

File test will be renamed into test.bak (same directory)

```
mv /home/frank/test{,.bak}
```

irssi

config

Server+nick:

```
irssi -n NICK #start irssi with nickname
```

```
/network add -nick NICK -autosendcmd "/msg nickserv IDENTIFY *****" fn  
/server add -auto -ssl -network fn chat.freenode.net 7070 #ports 6697, 7000  
and 7070 for SSL-encrypted connections.
```

```
/SET nick xxx  
/SET alternate_nick xxx  
  
/nick alternatenick  
/msg NickServ IDENTIFY mainnick password  
/msg NickServ GROUP
```

<https://freenode.net/kb/answer/registration>

```
/alias nick_recover msg NickServ GHOST $0 $1; wait 2000; msg NickServ  
RELEASE $0 $1; wait 2000; nick $0; wait 2000; msg NickServ IDENTIFY $1  
/network modify -autosendcmd "/nick_recover NICK PASSWORD" fn  
/SET server_reconnect_time 300
```

<https://irssi.org/documentation/startup/>

switch windows

```
/window 1-x #1=server-window
```

Ctrl+P (previous)/ctrl+N (next)

```
/win list #shows open windows in the Server-Status (1)
```

Away mode

```
/away grund #start awaymode (Nachrichten shown in Server-window #1)
```

```
/away #stop away mode
```

udev

same serial-adapter with Symlink based on USB-Ports (behind Hub)

<https://askubuntu.com/questions/49910/how-to-distinguish-between-identical-usb-to-serial-adapters>

```
udevadm info --attribute-walk --path=/sys/bus/usb-serial/devices/ttyUSB0
```

/etc/udev/rules.d/11-ttyusb.rules:

```
#r2 (first port) roothub-port.hubport
#   KERNELS=="1-3.1:1.0"
#   KERNELS=="1-3.1"
#r64 (second port=3)
#   KERNELS=="1-3.3:1.0"
#   KERNELS=="1-3.3"
KERNEL=="ttyUSB*", KERNELS=="*-.1*", SYMLINK+="ttyUSB_R2"
KERNEL=="ttyUSB*", KERNELS=="*-.3*", SYMLINK+="ttyUSB_R64"
```

my current config splitting by serial

```
#ch340 KERNELS=="1-3.3" no serial
SUBSYSTEM=="tty", ATTRS{idVendor}=="1a86", ATTRS{idProduct}=="7523",
SYMLINK+="tty_r2pro"
#cp2102 KERNELS=="1-3.2"
SUBSYSTEM=="tty", ATTRS{idVendor}=="10c4", ATTRS{idProduct}=="ea60",
ATTRS{serial}=="010CB6FA", SYMLINK+="tty_r3"
#cp2104 KERNELS=="1-3.1"
SUBSYSTEM=="tty", ATTRS{idVendor}=="10c4", ATTRS{idProduct}=="ea60",
ATTRS{serial}=="0001", SYMLINK+="tty_r2"
```

sshd

qnap (entware)

```
nano /opt/etc/ssh/sshd_config #ggf. optionen anpassen (hostkey
ecdsa/ed.../...)
ps | grep ssh
kill PID #PID= pid von /opt/sbin/sshd
/opt/sbin/sshd -E /tmp/sshd.log -o LogLevel=DEBUG3
tail -f /tmp/sshd.log
#bei Fehler "Bad ownership":
```

```
chmod go-w ~/;chmod 700 ~/.ssh;chmod 600 ~/.ssh/authorized_keys
#wenn fertig
/opt/etc/init.d/S40sshd restart
```

kernel kernelconfig (/proc/config.gz)

```
# modprobe configs
# zcat /proc/config.gz | grep -i hwmon
CONFIG_HWMON=y
# CONFIG_HWMON_DEBUG_CHIP is not set
# CONFIG_SENSORS_IIO_HWMON is not set
CONFIG_THERMAL_HWMON=y
```

mv-alternative

```
rsync -avh --progress --remove-source-files source target/
#delete empty directories (not done by rsync)
find source/ -type d -empty -delete
```

other

force fsck

in kernel-cmdline:

```
fsck.mode=force
```

smartctl / hdparm

```
smartctl -t short /dev/sdb
smartctl -a /dev/sdb | grep -A1 "Self-test execution status"
#warten bis fertig und bei Fehler:
smartctl -a /dev/sdb | grep '^#'
#sektor und angrenzende in Schleife versuchen neu zu schreiben
for i in {1709860..1709870};do hdparm --yes-i-know-what-i-am-doing --repair-
sector $i /dev/sdb;sleep 1;done
```

rc.local

<https://www.troublenow.org/752/debian-10-add-rc-local/>

VNC-Server

based on <https://www.scivision.dev/vncserver-setup-on-ubuntu/>

```
apt install tightvncserver openbox
apt install lxterminal firefox-esr --no-install-recommends
```

~/vnc/xstartup

```
#!/bin/sh
xrdb $HOME/.Xresources
xsetroot -solid grey

unset SESSION_MANAGER
exec openbox-session &
```

~/startVNC.sh

```
#!/bin/sh
vncserver :1 -geometry 1024x768 -depth 8
```

do not forget to set execute rights

```
chmod +x ~/startVNC.sh ~/.vnc/xstartup
```

i setart the script with rc.local (see above), but a init-script is also possible

<https://www.digitalocean.com/community/tutorials/how-to-install-and-configure-vnc-on-ubuntu-18-04-de>

locales

```
/usr/bin/locale: Cannot set LC_ALL to default locale: No such file or directory
```

Solution:

if not yet done, generate locales

```
locale-gen de_DE.UTF-8
```

add this to /etc/environment:


```
LC_ALL=de_DE.UTF-8  
LANG=de_DE.UTF-8
```

maybe again

```
dpkg-reconfigure locales
```

now error should be fixed

```
locale -a
```

Solution using /etc/default/locale was not working for me

From:

<https://wiki.fw-web.de/> - **FW-WEB Wiki**

Permanent link:

<https://wiki.fw-web.de/doku.php?id=en:linux:start&rev=1668939956>

Last update: **2023/06/08 17:06**

